




## LED EINSATZ DIY-9 | MODULO LED

> Ersatz für Serie BD12 ... | Sostituto per Serie BD12 ...




|                                                                                                                         |                |
|-------------------------------------------------------------------------------------------------------------------------|----------------|
| <b>SERIE</b>                                                                                                            | <b>BD9</b>     |
| <b>POWER</b>                                                                                                            | 9,5 W          |
| <b>LUMEN</b>                                                                                                            | 1250 - 1320 lm |
| <b>CREE COB</b>                                                                                                         | 250 mA - 36 V  |
| <b>CRI / RA</b>                                                                                                         | > 90           |
|  <b>68 MM AUSSCHNITT</b><br>FORO 68 MM |                |



Lebensdauer | vita: L80 B10 50.000h

## OHNE NETZTEIL | SENZA ALIMENTATORE



| Art. Nr.   | W     | Lm   | K      | Driver |
|------------|-------|------|--------|--------|
| BD9-275025 | 9,5 W | 1250 | 2700 K | /      |
| BD9-305025 | 9,5 W | 1280 | 3000 K | /      |
| BD9-405025 | 9,5 W | 1320 | 4000 K | /      |


## TRIAC DIM NETZTEIL | ALIMENTATORE TRIAC DIM

| Art. Nr.       | W    | V in          | Amp. | V out       | Amp. out | IP    | ta            | Dimensions       | VP |
|----------------|------|---------------|------|-------------|----------|-------|---------------|------------------|----|
| B96-PE294R4225 | 10 W | 200 - 240 VAc | /    | 25 - 42 VDC | 250 mA   | IP 20 | -20 ... +60°C | 115 x 40 x 26 mm | /  |

andere Dali/KNX Driver | altri Dali/KNX driver:


> Siehe [www.brilux.it/driver-dimmer](http://www.brilux.it/driver-dimmer) | visita [www.brilux.it/driver-dimmer](http://www.brilux.it/driver-dimmer)

## LICHTVERTEILUNG | DISTRIBUZIONE DELLA LUCE



## DIMMER

|        |                                                         |             |
|--------|---------------------------------------------------------|-------------|
| Schalk | Universal Tastdimmer<br>Regolatore a tasti universale   | ETD U2      |
|        |                                                         | ETD 2E      |
| Eltako | Universal-Dimmschalter<br>Dimmer universale elettronico | EUD61NPN-UC |
|        |                                                         | EUD12NPN-UC |



## ZUBEHÖR INNENRINGE | ACCESSORI ANELLI INTERNI



**BD12-RIC75..**  
Ring konisch  
Anello conico



**BD12-RIF75..**  
Ring flat  
Anello flat



**BD12-RIR75..**  
Ring abgerundet  
Anello curvato