

AL3 DRIVER LED CC / CV



SERIE ALVIT | B96-AL3

**Ausgang: CC (Konstant-Strom) /
CV (Konstant-Spannung)**

**Uscita: CC (corrente costante) /
CV (tensione costante)**

LED Netzteil On / Off
LED Alimentatore On / Off



EIGENSCHAFTEN | CARATTERISTICHE

Art. Nr.	W	V in	Amp.	V out	Amp. out	IP	ta	Dimensions	VP
CC (Konstant-Strom Corrente costante)									
B96-AL335CC	5,6 W	220 - 240 VAc	/	3 - 16 VDc	350 mA	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
B96-AL350CC	6 W	220 - 240 VAc	/	3 - 11 VDc	500 mA	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
CV (Konstant-Spannung Tensione costante)									
B96-AL312CV	6 W	220 - 240 VAc	/	12 VDc	0,5 A	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
B96-AL324CV	6 W	220 - 240 VAc	/	24 VDc	0,25 A	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60

