

DLX SMART HOME DIMMER CC/CV



BCA-DLX1224-4CC



BCA-DLX1224-4CV

SERIE SMART HOME | BCA-DLX

**Ausgang: CC (Konstant-Strom) /
CV (Konstant-Spannung)**

**Uscita: CC (corrente costante) /
CV (tensione costante)**

BLUETOOTH DIMMER CASAMBI 4CH

PUSH DIMMING

CASAMBI



EIGENSCHAFTEN | CARATTERISTICHE

Art. Nr.	W	V in	Amp.	V out	Amp. out	IP	ta	Dimensions	VP
CC (Konstant-Strom corrente costante)									
BCA-DLX1224-4CC3	24 - 48 W	12 - 24 VDC	/	12 - 24 VDC	4 x 350 mA	/	-10°C ... +40°C	88 x 54 x 25 mm	/
BCA-DLX1224-4CC7	24 - 48 W	12 - 24 VDC	/	12 - 24 VDC	4 x 700 mA	/	-10°C ... +40°C	88 x 54 x 25 mm	/
CV (Konstant-Spannung tensione costante)									
BCA-DLX1224-4CV	120 - 240 W	12 - 24 VDC	/	12 - 24 VDC	4 x 5 A	/	-10°C ... +40°C	88 x 54 x 25 mm	/

